

Bluetooth Touch Keypad PIX-PCH3-BT EM+MF

- 😤 Waterproof, conforms to IP66
- 🖄 Metal housing, anti-vandal
- Tard type: 125KHz EM Card & 13.56MHz Mifare Card
- 🖄 iOS and Android available
- 🖄 Add / Delete users by APP
- 😤 Support checking Opening Record
- Support Gateway
- * Multiple Access Modes: Smartphone, Card, PIN




The PIX-PCH3-BT EM+MF is a Bluetooth-enabled waterproof touch keypad + RFID access controller. It's integrated with Tuya which supports 100 users (including 255 card/ PIN users). It's available for both iOS and Android.



Compatible with all Bluetoothenabled mobile phones (version: 4.0 above)



Various methods to open the door, make it easy and safe entrance








Dual-frequency: support 125KHz EM & 13.56MHz Mifare cards simultaneously

Support Adding / Deleting Users by APP







Support Viewing Opening Record

Support Gateway






APP name: 'TuyaSmart' available both for iOS and Android



User Capacity Common User Visitor User Panic User	Hardware User: 1000 APP User: 100 (including 255 card/ PIN users) 988 10 2
PIN Length	4~6 digits
Operating Voltage	12~18V DC
Idle Current	≤ 60mA
Active Current	≤ 150mA
Proximity Card Reader	EM & Mifare
Radio Technlogy	125KHz & 13.56MHz
Read Range	2~6cm
Wiring Connections	Relay output, exit button, alarm, door contact, Wiegand input/output
Relay	One (NO, NC, Common)
Adjustable Relay Output Time	0~99 Seconds (5 seconds default)
Lock Output Load	2 Amp Maximum
Wiegand Interface PIN Output	EM card : Wiegand 26~44 bits input & output (Factory default: Wiegand 26bits) Mifare card :Wiegand 26~44 bits,56bits,58bits input & output (Factory default: Wiegand 34bits) 4 bits,8bits (ASCII),10 digits Virtual Number(Factory default:4bits)
Environment	Meets IP66
Operating Temperature	-40°C ~ 60°C (-40°F ~ 140°F)
Operating Humidity	0%RH ~ 98%RH
Physical	Zinc-Alloy
Color	Sliver & Black
Dimensions	L148 x W43.5 x H22 (mm)
Unit Weight	330g
Shipping Weight	405g



Product Size









Biometric Devices RFID Fingerprint | Face | Card | Access PIN Reader Electromagnetic Lock Exit Button | Break Glass Video Door Intercom





PIXELS CONNECT PTE LTD

1013, Geylang East Ave 3, #01-144 Singapore 389728 pixelsconnect@gmail.com | www.pixelsconnect.com.sg | Tel:+65 6440 0023

PIX-PCH3-BT EM+MF (BLUETOOTH TOUCH KEYPAD)

PIXELS CONNECT PTE. LTD.