

PIXELS CONNECT PTE LTD

Outdoor Keypad, H&EM Reader PIX-PCSK5-H&E

- * Metal case, anti-vandal
- * Waterproof, conforms to IP66
- ★ One relay, 1000 users
- ★ Wiegand 26~37 bits input & output
- User data can be transferred by Wiegand line
- Access modes: Card, PIN, Card + PIN, Multi Cards/PINs
- Card type: 125KHz Hid & EM card, PIN length: 4~6 digits
- Pulse mode, toggle mode
- 2pcs device support interlock for two doors




The PIX-PCSK5-H&E is a single door multifunction standalone access controller or a wiegand output reader. It supports 1,000 users (998 common users + 2 panic users), all user data can be transferred from one to antother (Max 10pcs).





PIXELS CONNECT PTE LTD



Three working modes-Wiegand 26~37 bits input & output




User Capacity	1000
Common User	998
Panic User	2
Operating Voltage	9~18V DC
Idle Current	< 35mA
Proximity Card Reader	Hid & EM
Radio Technology	125KHz Proximity Card
Read Range	2~6 cm
Wiring Connections	Relay output, exit button, alarm, door contact, Wiegand input, Wiegand output
Relay	One (NO, NC, Common)
Adjustable Relay Output Time	0~99 Seconds (5 seconds default)
Lock Output Load	2 Amp Maximum



PIXELS CONNECT PTE LTD

Wiegand Interface	Wiegand 26~37bits
Wiegand Input	26~37bits
Wiegand Output	26~37bits
PIN Output	4 bits, 8 bits(ASCII), 10 digits Virtual Number
Environment	Meets IP66
Operating Temperature	-40 °C ~ 60 °C (-40 °F ~ 140 °F)
Operating Humidity	0%RH ~ 98%RH
Physical	Zinc Alloy
Color	Silver
Dimensions	14.8L x 5.6W x 2.25H (cm)
Unit Weight	285g
Shipping Weight	350g

Product Size







Analog Camera, IP Camera Dome & Bullet Cameras Hidden Cameras IK Cameras PTZ Cameras



4K Action Camera | Car Camera Battery Cameras WiFi Door Bells Hidden Cameras



Fingerprint | Face | Card | Access PIN Reader Electromagnetic Lock Exit Button | Break Glass Video Door Intercom



PIXELS CONNECT PTE LTD

1013, Geylang East Ave 3, #01-144 Singapore 389728 pixelsconnect@gmail.com | www.pixelsconnect.com.sg | Tel:+65 6440 0023